

Publication number:

0 195 630

A2

13

# **EUROPEAN PATENT APPLICATION**

(21) Application number: 86301926.1

(3) Int. Cl.4: **G 02 B 6/00 G 02 B 6/20** 

(22) Date of filling: 17.03.88

30 Priority: 18.03.85 US 713150

4 Date of publication of application: 24.09.88 Bulletin 88/38


(94) Designated Contracting States: AT BE CH DE FR GB IT LI LU NL SE 1) Applicant: LAAKMANN ELECTRO-OPTICS INC. 33052 Calle Aviador, Suite B San Juan Capistrano California 92675(US)

12 Inventor: Laskmann, Katherine Dexter 23821 Daysa Circle Laguna Niguel California(US)

(14) Representative: Colgan, Stephen James et al. CARPMAELS & RANSFORD 43 Bloomsbury Square London WC1A 2RA.(GB)

4 Hollow waveguide having plured layer dielectric.

(5) A hollow waveguide has an inner reflective layer such as silver, overcoated with plural layers of dielectric. Preferably three dielectric layers are used, with the inner two having quarter wave thickness, and the outer one having one half on one and one half the quarter wave thickness. Compositions for the dielectric include ThF /Ge/ThF ZnSe/Ge/ZnSe, Ge/ ThF/Ge, and ThF/ZnSe/ThF.



#### HOLLOW WAVEGUIDE HAVING PLURAL LAYER DIELECTRIC

#### Technical Field

5

This invention relates generally to flexible, narrow diameter, hollow waveguides and, in particular, to those capable of high efficiency transmission of CO<sub>2</sub> laser energy suitable for medical applications.

10

# Cross Reference to Related Applications

Reference is made to concurrently filed, commonly assigned patent applications, both of K. D. Laakman, respectiv ly entitled "Hollow Waveguide" (U.S.Serial No.713,149) and "Hollow Waveguides Having Disparate Dielectric Overcoatings" (U.S. Serial No. 713,151).

#### Background of the Invention

20

15

for almost as long as CO<sub>2</sub> lasers have been viable tools for medical applications, the search has been on for improved modes of guiding the laser beam to the desired operating area. For the most part, lasers have been coupled with multi-section articulated arms having any number of large bore tubular sections hinged together with a reflective surface at each hinge to permit the laser light to traverse the length of the arm and to be aimed toward the desired site.

30

35

While such articulated arm laser systems have experienced wide spread acceptance lately in a variety of medical specialities, they are generally somewhat clumsy to use since the arm typically offers some "resistance" to mov - ment by the surgeon. Such arms are inherently limited in

the scope of their medical applications, because of their size and limited flexibility. Present CO<sub>2</sub> surgical applications are essentially limited to those in which there is direct access to the area to be treated. CO<sub>2</sub> endoscope procedures are still rare, as the present technology requires a relatively wide, but short and straight endoscopic channel to "shoot" the CO<sub>2</sub> beam down. In addition, most articulated arms experience problems with heam alignment particularly if the surgical application calls for a small spot size. These arms also tend to be expensive, especially if precision optical alignment is required.

It is an object of the present invention to provide a small diameter, flexible fiber for carrying CO<sub>2</sub> laser emissions, which can be threaded down a longer, narrow or flexible endoscope, or alternatively be used as a second puncture probe.

20 A variety of optical fibers have been proposed as the transmission medium for laser energy, but to date, not a single one has become commercially accepted for the 10.6 micron wavelength which is characteristic of CO2 lasers. Optical fibers or light pipes for the transmission of infrared light at 10.6 microns have however been 25 proposed: in one instance a polycrystalline fiber, such as the KRS-5 fiber developed by Horiba, Ltd. of Japan; and in another, a flexible, hollow waveguide, various versions of which have been suggested by among others E. Garmire and M. Miyagi. See, for instance, M. Miyagi, et al., 30 \*Transmission Characteristics of Dielectric-Coated Metallic Waveguide for Infrared Transmission: Slab Waveguide Model\*, IEEE Journal of Quantum Electronics, Volume QE-19, No. 2, February 1983, and references cited therein. Recently, Miyagi, et al. sugg sted fabricating a 35 dielectric-coated metallic hollow, flexible waveguide for

IR transmission using a circular nickel waveguide with an inner germanium layer applied by rf-sputtering, plating and etching techniques. Miyagi, et al. predict extremely small transmission losses for a straight guide, but in fact, actual transmission degrades substantially with but nominal bending radii (20 cm). To understand this, the mechanism of transmission must be considered.

Transmission of laser light through a flexible, narrow diameter hollow waveguide is subject to loss- largely due 10 to successive reflections of the beam along ...e interior surface of the curved quide. For the size and curvatures contemplated for a medical fiber, rays will intersect the wall at angles of incidence ranging from, typically, 80° to 90°. Bending a hollow fiber increases the loss as it 15 tends to increase the number of internal reflections and decrease the angle of incidence. In general, as the angle of incidence decreases from 90° to 80°, the loss per reflection bounce increases. It is an object of the present invention, therefore, to provide a coating which 20 has him reflectivity over angles of incidence ranging from 80 to 90°.

A difficulty of curving metal walls is that at these angles of incidence, metals tend to exhibit high reflecti-25 vity for only the S polarization but low reflectivity (<96%) for the P polarization. The losses for a 1 meter curved guide are of the order 10 dB. Garmire et al. attempted to avoid this problem by using a metal/dielectric guide in which the guide was oriented relative to 30 the incoming beam such that the metal walls "saw" only the P polarization. This approach is flawed, however, because the dielectric walls show high reflectivity for only very, very high angles of incidence, typically in excess of 89°--requiring, in ess nce, that the guide must be straight 35 along the dir ction of the dielectric.

Some have suggested remedying this situation by overcoating a reflecting surface with a quarter-wave dielectric coating. Such a coating will yield high reflectivity for the P polarization, but low for the S polarization.

- Miyagi et al. attempt to strike a compromise by choosing a coating of thickness somewhere between those favoring the P and and those favoring the S polarization. He chose a germanium coating of approxiamately 0.4 to 5 micrometers in thickness. This coating yielded relatively good results (>90%/meter transmission) for straight guides, but
- This disparity appears to result from two factors: 1) The transmission with the He<sub>11</sub> mode in a straight guide correlates poorly with the transmission of very high multi order modes in a bent guide; and 2) The imaginary part of the refractive index of the dielectric coating is extremely crucial in the transmission of a bent guide.
- 20 It is an object of the present invention to provide dielectric overcoated waveguides which are tuned to perform well although bent in compound curvature.

#### Summary of the Invention

rather poor for bent guides.

25

30

we have invented a flexible, narrow outer diameter, metal coated dielectric-overcoated hollow waveguide capable of transmitting in excess of 68% of the entering CO<sub>2</sub> laser energy over a one meter section even when subjected to compound curvatures. The waveguide is sufficiently thin to be passed down the esophagus of an adult patient and is safe for endoscopic applications.

The principles of the present invention, like these in th aforementioned concurrently filed applications, are premised on dealing with refractivity as a complex (i.e.,

real plus imaginary) quantity, taking into account both P and S polarizations over a designated range of angles of presentation. In accordance with the former aforementioned concurrently filed application, entitled simply "Hollow Metal Waveguide" (LAK-7), a flexible, narrow diameter, hollow waveguide has an outer reflective structure coated on its inner walls with suitable dielectric material of thickness equal to about one eighth the wavelength of the light to be transmitted by the waveguide. Such a dielectric construction will, on average, have relatively minimal adverse effect (i.e., loss) for both P and 3 polarizations, because the extinction coefficient of the complex index of refraction will have been reduced substantially over the quarter wave thickness shown in the prior art. For example, thorium fluoride (ThF,) and zinc selenide (2nSe) are disclosed as suitable dielectric materials for transmission of CO2 laser emissions. In such preferred embodiments, silver is an appropriate reflecting outer layer, and the dielectric thickness may be within about 40% of an eighth wavelength in thickness.

The principles of the present invention feature plural dielectric overcoatings of select materials and thickness to promote transmission of laser energy through a flexible (i.e., bent) waveguide. Preferably, three thin film coatings of two different dielectric materials will have the first and third coatings of the same, relatively low index of refraction (e.g., ThF, or ZnSe), with the intermediate layer having a relatively high index of refraction (e.g., Ge). For example, this arrangement may include the layer first contacting the beam having a thickness of either about one and one-half times (±0.2) the thickness of a quarter wave layer, or one-half (±0.2) of a quarter wave thickness for the laser energy in the medium of the low index dielectric. In such instance, the two inner layers have quarter wave thickness. It is also feasible

10

15

20

25

30

to have germanium constitute the first and third layers, and ThF, constitute the intermediate layer.

#### Brief Description of the Drawings

Fig. 1 is a diagrammatic representation of a section of a curved light pipe illustrating schematically the multiple reflections to which a coherent lightwave is subjected while travelling through the light pipe;

10

5

Fig. 2 is a straight section of a portion of a hollow metal waveguide according to the present invention;

Fig. 3 is a section taken along line 3-3 of Fig. 2;

15

Fig. 4 is an enlarged section taken along line 4-4 of Fig. 3;

Fig. 5 is a view similar to Fig. 3 representing an alter-20 native embodiment of the waveguide; and

Fig. 6 is a view similar to Fig. 3 showing another alternative embodiment of the waveguide.

25

# Detailed Description of the Preferred Embodiments Including the Best Mode for Carrying Out the Invention

30

35

In general, for a guide to be feasible for medical including endoscopic applications, the average reflectivity of P and S polarizations combined must be greater than 97% and preferably greater than 99% for both P and S polarizations for all angles of incidence from ab ut 80° to about 90°. The reason for requiring a high reflectivity c ndition

over such a broad range of angles is that a curved guide in effect introduces lower angles of incidence as the heam is propagated through the guide. The extreme angle of incidence Ø that needs to be considered in a curved guide of inner cross section d and radius of curvature R is given by the relationship:

$$\emptyset = \cos^{-1} \sqrt{2d/R}$$

Hence, for a guide with d = 1 mm and R = 10 cm, the extreme incident angle is 82°. A waveguide in actual medical use will have, of course, a non-uniform radius of curvature introducing in effect even smaller incident angles. However, for a waveguide with an inner cross section diameter on the order of 1 mm the angles of incidence will normally be in the 80° to 90° range.

In practice, a portion of the waveguide will have compound curvatures such as shown in the diagrammatic illustration 20 of Fig. 1 wherein the laser beam, modeled in Figs. 1 and 2 as a one dimensional ray, enters the waveguide in a direction normal to a plane orthogonally intersecting the waveguide at one end of the guide. The beam is then reflected off the interior surface of the waveguide at intervals determined by the curvature of the guide. For 25 the types of guides under consideration, i.e., those having an inner diameter of about 1 mm and curvatures of 30 cm or less , a typical ray will hit the interior wall about every 1 to 2 cm. Hence, for a one meter length of the guide there will be about 75 reflections or bounces. 30 Assuming an average energy loss of 0.5% per bounce, a one meter guide will transmit 68% of the light entering the guide. With just a 'lf percent increase in loss per bounce to 1%, the overall transmission falls to about 47%. 35

For purposes of this application, "transmission rating" shall describe the percentage of CO<sub>2</sub> laser energy transmitted by a one meter section of a curved guide. Thus, a 68% transmission rating represents a one meter section of a guide that transmits at least 68% of the energy of a propagating CO<sub>2</sub> laser beam entering the guide after the beam is subjected to up to 75 internal reflections.

With reference to Figs. 2, 3, and 4, there is shown various aspects of a straight line section of a flexible 10 hollow waveguide referred to generally as 10. The waveguide includes tube 20 of a material, preferably stainless steel or aluminum, chosen on the basis of mechanical performance including ductility and strength hygroscopicity. Within the tube 20 are matable metallic 15 halves 25 and 26 which when mated as shown form the hollow rectangular guide. Each half may be milled from a wire, and have a groove or "V" coined therein, as shown. An additional requirement of the halves 25 and 26 is that they easily coatable, for example, in a vacuum chamber by 20 an adhesive material, to yield a low loss surface. The inner walls of the halves 25 and 26 must also be optically smooth, relative to grazing incidence at 10.6 um. Onto the interior surface of the guide a metal coating 30 is applied. Coating 30 must be a high normal incidence reflector of light at a wavelength of 10.6 microns, such as silver. Other suitable metal coatings include gold and aluminum. The thickness of the silver coating 30 is not critical and is preferably in the range of something less than approximately 100 angstroms. To improve the bonding 30 between silver coating 30 and the substrate 25 and 26, a high adhesion coating 40, preferably of chromium, is applied onto the tube prior to the application of the silver coating. With the silver coating 30 bonded to the m tal sub trate, a multiple layer 51, 52, 53 forms a thin 3.5 film dielectric coating 50.

As above stated in general terms, the present invention features a layered dielectric overcoat which is a function of  $\lambda_m$ , the wavelength of the light in the medium at the 80° angle of incidence. More precisely,

5

$$\lambda_{\rm m} = \frac{\lambda}{\bar{n}} \frac{1}{1 - \frac{\sin^2 80^{\circ}}{n^2}}$$

10

15

20

25

where  $\lambda$  is the wavelength of the same light in a vacuum and n is the index of refraction.

The losses obtained for a variety of dielectric coatings are influenced by the thickness of the coating as well as by N, the complex index of refraction of the material. N is given by n + ik, where the extinction coefficient k is the imaginary part, related to the absorption properties of the material. The real part, n, commonly referred to simply as the index of refraction, is the ratio of the speed (or wavelength) of light in a vacuum to the speed (or wavelength) of light in the material. Losses are lower as the imaginary component, k, of the refractive index is minimized. It is crucial to the performance (i.e. transmission) of the waveguide to keep the value of k to some low number. Even though k is related to th properties of the material, to a significant degree the magnitude of k is quality controllable through proper vacuum deposition techniques.

30

35

The principles of the present invention, relating to plural layer dielectrics, may be usefully considered by comparison with single layer guides in accordance with th former copending application (LAK-7). Tables 1-6 as follows, and their discussion, are duplicated from LAK-7.

As the value of k decreases, the greater the tolerance allowed on the coating thickness. For example, with a single ThF, layer with a k = 0, thickness in the range from about .6 $\mu$  to about 2.3 $\mu$  (or alternatively .2 to .8  $\lambda_{\rm m}/2$ ) will yield an average reflectivity of P and S combined greater than 99% from 80° to 90°. On the other hand, with k = 2 x 10<sup>-3</sup>, the thickness may only be from about .4 to .6  $\lambda_{\rm m}/2$  to still yield the same minimum limit on reflectivity. Tables 1 through 3 illustrate this comparison in detail.

TABLE 1

		Loss of	E Silver	of Silver coated with ThF, with loss-less ( $k = 0$ ) ThF,.	The, wi	th loss-	less (k =	0) ThF4.		
	Ħ	. 58µ	•	= 1.16µ	T - 1.	67 и	T = 2	.23μ	T	2.79
ngle	Loss P	Loss S		Loss P Loss S	Loss P	Loss P Loss S	Loss P	Loss P Loss S	Loss P	Los
80	1.76	.14	. 77	.18	.54	.32	.50	.84	.50	Э.
83		.09			. 39	.22	.35	.62	.35	4
86		. 05			. 23	.13	. 20	.37	. 20	4
89		.01			90.	.03	.05	60.	.05	7
	•									

TABLE 2

Loss of Silver coated with ThF, of varying thickness, with  $k = 2 \times 10^{-3}$ .

)	Angle	T = Loss P					1.8 µ Loss S		
10	-	2.79 2.64 2.25 1.56	.10 .07 .04	1.55 1.30 .99 .62	.19 .13 .08	.91 .67 .41	.72 .56 .41 .25	.80 .58 .35	3.28 2.52

15

# TABLE 3

Loss of Silver coated with ThF, of varying thickness, with  $k = 10^{-3}$ .

	Angle						1.8 µ Loss S		
25	81	2.46	.13	1.26	.21	.86	.53	.73	2.57
	83	2.32	.10	1.05	.16	.69	.49	.58	2.18
	85	1.98						.42	1.68
	87	1.37	.04	.50	.07	.31	.18	.26	1.06
	89	.49	.01		.02		.06	.09	.36 .
20			_						

30

Similar dependence of allowable coating thickness on k value can be found with ZnSe as illustrated in Tables 4 and 5.

35

# TABLE 4

40 Reflection loss of  $A_g$  coated with ZnSe of varying thickness in which  $k=10^{-3}$ .

	Angle	T -		T =		T - Loss P		_	Loss S
45	81 83	3.99 4.68		1.98 1.76		1.16	.34 .26	.92 .72	
50	85 87 89	5.43 5.62 2.98	.06 .04 .01	1.41 .92 .32	.05	.42	.19 .11 .06	.52 .31 .10	

#### TABLE 5

Reflection loss of Ag coated with ZnSe of varying thickness, in which  $k = 10^{-3}$ .

	Angle	T =	.lu Loss S	T = Loss P	.4 µ Loss S	T - Loss P	.7 µ Loss S	T =	l.0 µ Loss S
10	81 85 89	3.97 5.40 2.97	.06	1.37	.09	.65	.18	.46	1.06

Even with k = 0, for high refractive indices, unacceptably high reflectivity losses occur. Germanium, for exampl, even with k = 0 never yields a low loss reflectivity condition as can be seen in Table 6.

# TABLE 6

20

Reflection loss of  $A_g$  coated with Ge and varying thicknesses in which k = 0.0

25	Angle	T =	.lu Loss S					T = Loss P	
	81 83	4.04 4.65	.12	2.75		2.31			11.07
	85	5.23	-	1.99		1.63	.47	1.48	7.26
30	87 89	5.11 2.52	.04	1.31 .46	.07 .02		.28 .09	.64 .21	4.63 1.60

When the k values can be controlled to be less than about 2 x 10<sup>-3</sup> n, it becomes advantageous from a performance view to consider multiple layer dielectrics pursuant to th present invention. There are a wide range of coating designs which, if the k value can be kept small, will yild quite acceptable results. From computer modelling,

we have found a wide range of possible coatings ranging from 2 layers to 3 layers and coating thicknesses of substantial variations. Indeed, we found no way we can analytically give a convenient formula for stating the good coating design—short of actual computer modelling.

In the preferred embodiment illustrated in Fig. 4, there is shown three layers of thin film dielectric coatings with the inner and outer layers 51 and 53 being, for example,  $ThF_4$  with the middle layer 52 of Ge. As shown in Table 7, Case 3, superior results are obtained for the range of incident angles 81° to 89° by reducing the coating thickness of the final (outer)  $ThF_4$  layer 53 to about 40% from the  $1/4\lambda$  thickness to about 1.67 $\mu$  and using  $1/4\lambda$  thicknesses for the other two layers 52 and 51.

#### TABLE 7

Percent loss of silver coated with  $ThF_4/Ge/ThF_4$  stack of varying thicknesses,  $k=10^{-3}$  for all three layers.

#### Percent Loss

		Cas	e 1		se 2		Case 3		se 4
. 2	5 Angle	Loss P	Loss S	Loss P	Loss S	Loss	P Loss S	Loss P	Loss S
	81	.52	6.07	.52	.90	.61	.20	.99	.07
	83	.42	7.14	.42	.73	.50	.15	.76	.05
	85	.30	8.44	.31	.54	.38	.11	<b>.</b> 59	.04
30	87	.18	8.74	.19	.33	.23	.07	.38	.02
30	89	.08	4.76	.06	.11	.08		.13	.01
	Case	1: 2	.79 um,	.67 1	ım, 2.79	mu e	(all thr	ee-qua	erter wave)
	Case	2: 2	.32 µm,	.67	յու, 2.79	9 μm	(all two	-quar	ter wave)
3.5	5 Case	3: 1	.67 um,	.67 i	ım, 2.79	9 um	(all two	-quar	ter wave)
	Case	4: 1	.16 um,	.67	ım, 2.79	9 µm	(all two	-quar	ter wave)

As Table 7, Case 3, above suggests the maximum loss is a modest .61 percent at 81° and the mean loss is substantially less than 0.5 percent per reflection. Good r sults

5

. 10

are also obtained using the same sequence of coatings as in the above example, but with the outermost ThF layer 53 about 40 percent thicker than a 1/4\(\lambda\) design. As the results indicate in Table 8, the maximum loss was .98 percent, again at 81°.

#### TABLE 8

Percent loss of silver coated with ThF<sub>4</sub>/Ge/ThF<sub>4</sub> stack of varying thicknesses.

#### Percent Loss

		Ca	se 1	Ca	se 2	Ca	se 3
15	Angle	Loss P	Loss S	Loss P	Loss S	Loss P	Loss 5
	81	.62	2.62	.86	.98	1.49	.57
	83	.49	2.46	.68	.82	1.20	.47
	85	.35	2.08	.49	.63	.87	.35
20	87	.21	1.43	.30	.39	.53	. 21
	89	.07	0.51	.10	.13	.18	.07

Case 1: 3.34 um, .67 um, 2.79 um Case 2: 3.90 um, .67 um, 2.79 um

25 Case 3: 4.46 µm, .67 µm, 2.79 µm

 $k_{Ge} = 2 \times 10^{-3}$   $k_{ThF_u} = 10^{-3}$ 

As in a single layer coating, we find extreme sensitivity to k value. Indeed, if k=0, three  $\lambda_m/4$  layers of ThF<sub>u</sub>/Ge/ThF<sub>u</sub> will yield extraordinarily low losses. As is shown in Table 9, there is a substantial increase in loss with this coating by having a finite k. If any generalization can be made, it is that at least one non-quarter wave coating is required when k values are even in the  $10^{-3}$  range. So long as k/n is smaller than about  $1.5 \times 10^{-3}$ , w found that the best of the single layer coatings were inferior to the best of the multiplulay r coatings.

-16-

TABLE 9

Percent loss of Silver coated with quarter wave  $ThF_{\mu}/Ge/ThF_{\mu}$  stack for k = 0 and finite k.

5

20

25

	•	P	ercent Los	<u> </u>	
		Ca	se l	Cas	e 2
		P	S	P	S
	Angle	Loss	Loss	Loss	Loss
10					
	81	.10	.21	.52	6.07
	83	.08	. 24	.42	7.14
	85	.08	. 28	.30	8.33
	87	.04	. 29	.18	8.74
15	89	.01	.16	.06	4.75

Other three layer stacks of dielectric coatings 50 were investigated besides the combination of Ge and  $ThF_{\psi}$ ; however, these produce the best results because of the large ratios of refractive index (4.0 versus 1.35).

One combination investigated was a ThF<sub>u</sub>/Znse/ThF<sub>u</sub> layer coated onto Ag. Here, it was found that there was quite a range of coating designs which yielded acceptable coating reflectivities, although none yielded as high performance as the optimized Ge/ThF<sub>u</sub>/Ge stack. One of the best performances occur when the first layer's thickness

is 1.16 (.4  $\lambda/4$ ), the second layer's 1.79 (.65  $\lambda/4$ ), and the third layer's 2.5 (.9  $\lambda/4$ ). This particular design yields a loss of .85% and .45% for the P and S polarization, respectively. A k value of 1 x  $10^{-3}$  was assumed for each layer.

Another design considered was a ZnSe/Ge/ZnSe stack coated onto a thin layer of silver. As with the other multiple layer coatings (ThF<sub>4</sub>/Ge<sub>1</sub>/ThF<sub>4</sub> and ThF<sub>4</sub>/ZnSe/ThF<sub>4</sub>), there are a wide range of coating designs (various layer thicknesses) which yield acceptable performances. One of the optimum coating designs with this stack are where the coatings are of the following thicknesses:

15 Layer 1 =  $.71\mu$  (.6  $\lambda m/4$ )

Layer 2 =  $.69\mu$  (1.  $\lambda m/4$ )

Layer  $3 = 1.19\mu \quad (\lambda m/4)$ 

With a k value equal to  $10^{-3}$  for each of the three layers, the reflection loss for the P and S polarization of 81° is computed to be .65% and .17%, respectively. Another good design is:

25

20

5

10

Layer 1 =  $.95\mu$  (.8  $\lambda m/4$ )

Layer 2 = .43 $\mu$  (.63  $\lambda$ m/4)

30 Layer 3 =  $1.19\mu (\lambda m/4)$ 

Here, the computed loss is .87% and .17%  $\mu$  at 81°.

Regardless of choice of dielectric coating materials, the preferred geometry of the metal guide 20 is square shaped as shown in Fig. 3 and in Fig. 5. In Fig. 3, respective halves have V-shaped grooves formed th rein, and the

square guide results when the opposing portions are joined. The square shape is particularly advantageous for ease of fabrication since two essentially V-shaped portions 20a and 20b may be separately coated and subsequently combined to form the guide. When V-shaped sections 20a and 20b are placed in a vacuum chamber, resting on their respective pointed ends 21 with their interior surface that is to be coated facing a source of thin film dielectric, a relatively equal thickness coating by the well-known vacuum deposition technique is achievable. A generally circular cross sectional guide such as shown in Fig. 6 may also be fabricated by joining semicircular sections 20'a and 20'b. However, the circular interior surface of sections 20'a and 20'b require that they be oscillated during the vacuum deposition step in order to ensure a relatively uniform thickness of the dielectric coatings.

After fabrication, the waveguide 20 is preferably inserted into a plastic or metal sleeve 60 for safety consideration should the guide ever crack during use. To enhance the ease with which metal guide 20 is encased in a plastic sleeve 60, the metal guide 20, as shown in Fig. 5, has a planar interior surface but has a circular exterior.

25

30

35

20

10

15

During fabrication, care should be taken to insure good layer-to-layer adhesion with minimal mechanical stresses in and among the layers. Excessive mechanical stresses will at the least degrade performance, and might even cause the coatings physically to fracture and flake. Stress conditions will be a function of material selection, coating thickness, and the coating process. For example, ThP, and Ge both are characterized by tensile stress, and thus in combination are more apt to have poor layer-to-layer adhesion. On the other hand, InSe is characterized by lower tensile str ss, which favors its combination with either ThF, or Ge.

• .

Almough the invention has been specifically exemplified with reference to dielectric coatings whose thicknesses have been calculated for use in waveguides designed for CO<sub>2</sub> lasers which lase at 10.6 microns wavelength, it will be appreciated that the invention is also applicable to waveguides for use with lasers operating at different wavelengths, with the dielectric coatings and their thicknesses being selected according to the criteria described above.

#### CLAIMS

5

20

25

- 1. A narrow diameter, flexible hollow waveguide for high efficiency transmission of laser light by internal reflection, said waveguide comprising:
  - (a) a hollow flexible elongated housing;
- (b) a metallic coating, highly reflective at normal incidence, on the internal surface of said guide;
  - c) plural layers of thin film dielectric coatings overlying said reflective coatings.
- 2. A waveguide as described in Claim 1 and comprising three said layers of dielectric, first and third ones of which being a first select dielectric material, and a middle one of which being a second select dielectic material.


3. A waveguide as described in Claim 2 wherein said first select dielectric material has an index of refraction which is relatively low in comparison with the index of refraction of said second select dielectric material.


- 4. The hollow waveguide according to Claim 2 wherein the first and third layers are ThP, and the second layer is selected from the group consisting of ZnSe and Ge.
- 5. The hollow waveguide according to Claim 2 wherein the first and third layers are ZnSe and the second coating is Ge.
- 6. The hollow waveguide according to Claim 2 wherein said first and third layers are Ge and the second layer is ThF<sub>L</sub>.


7. A waveguide as described in Claim 2 wherein said outermost of said dielectric layers has a thickness between approximately one-eighth and three-eights of the wavelength of light in said outermost layer.


- 8. A flexible hollow waveguide for high efficiency transmission of CO<sub>2</sub> laser light which comprises:
- (a) a guide having an internal surface and an
   external cross section sufficiently small to allow for endoscopic application;
- (b) a metal coating applied to the internal surface of said metal guide, said coating characterized by a high degree of reflectivity of light at normal incidence for the waveglength of use.;
- (c) a plural layer dielectric coating applied to said metal coating, said coating composite having the reflectivities of the P and S polarization averaged together to be in excess of 98.5% for all angles of incidence ranging from 80° to 90°.
- The hollow waveguide according to Claim 8 wherein said
   guide is made of aluminum and said metal coating is
   silver.
- 10. The hollow metal waveguide according to Claim 8 wherein the interior cross section of the waveguide is 30 square shaped.
  - 11. The hollow metal waveguide according to Claim 8 wherein the interior cross section of the waveguide is circular.


12. For use with a laser providing output laser radiation of a given frequency, a waveguide as claimed in any of claims 1 to 11.














(1) Publication number:

0 195 630 **A3** 

 $\odot$ 

#### **EUROPEAN PATENT APPLICATION**

(1) Application number: 86301926.1

(3) Int. Cl.<sup>2</sup>: **G** 02 **B** 6/20 G 02 B 6/00, G 02 B 6/10

22 Date of filing: 17.03.86

30 Priority: 18.03.85 US 713150


- 43 Date of publication of application: 24.09.86 Bulletin 85/39
- (9) Date of deferred publication of search report: 28.12.88
- 84 Designated Contracting States: AT SE CH DE FR GB IT LI LU NL SE

1) Applicant: LAAKMANNELECTRO-OPTICS INC. 33052 Calle Aviador, Suite B San Juan Capistrano California 92675(US)

- (72) Inventor: Laskmann, Katherine Dexter 23821 Daysa Circle Laguna Niguel California(US)
- (2) Representative: Colgan, Stephen James et al. CARPMAELS & RANSFORD 43 Bloomsbury Square London WC1A 2RA.(GB)

(A) Hollow waveguide having plural layer dielectric.

(57) A hollow waveguide has an inner reflective layer such as silver, overcosted with plural levers of dielectric. Preferably three dielectric layers are used, with the inner two having quarter wave thickness, and the outer one having one half on one and one half the quarter wave thickness. Compositions for the dielectric include ThF\_Ge/ThF., ZnSe/Ge/ZnSe, Ge: ThF/Ge, and ThF/ZnSe/ThF.





# EUROPEAN SEARCH REPORT

Application Number

EP 36 30 1926

Ĺ	DOCUMENTS CONSI	DERED TO BE RELEVA	NT		
Category	Citation of document with a of relevant pa	ndication, where appropriate, issages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int. C). 4)	
A	US-A-3 436 141 (G. * Column 2, lines 1	6-53; figure 3 *	2,11	G 02 B 6/20 G 02 B 6/00 G 02 B 6/10	
Y,D	136-145, IEEE; M. M "Transmission chara dielectric-coated m for infrared transm waveguide model" " Page 141, chapter	February 1983, pages HIYAGI et al.: cteristics of metallic waveguide mission: slab			
A	US-A-4 068 920 (M. * Claims 1,4,11,12;		1,8,10		-
A	Society of America; "Losses and phase of	s 4221-4226, Optical M. MIYAGI et al.: constant changes	1,4,5		1
	caused by bends in hollow waveguides f * Page 4225; append		TECHNICAL FIELDS SEARCHED (Int. C).4)		
A	JOURNAL OF LIGHTWAY LT-2, no. 2, April IEEE; M. MIYAGI et of dielectric-coate waveguides for infr " Page 124, chapter	1,2,8,9			
	-				
	The present search report has			Extenses	
TH	Place of shareh E HAGUE	Date of completion of the nearth 05-10-1988	PFAH	LER R.	
Y: 92 dd A: 10 O: n	CATEGORY OF CITED DOCUME reicularly relevant if taken alone reicularly relevant if combined with as cument of the same category chnological background on-written disclosure termediate document	sciple underlying the document, but public g date of in the application of for other reasons to same patent family	sà <b>c</b> l en, er	L	